AD54.30-P-6000-04GH	CAN data lines test electrics IC	Model 163		
---------------------	----------------------------------	-----------	--	--

^t A	Scope of test		ring instrur	ment/	Operation/ Requirement	Specified value	DPossible cause/ Remedy
1.0	CAN data buses Resistance	9 W (B.9)	b A1	L 10	Ignition: OFF Coupling "B" (12-pin) disconnected (N3 is connected to CAN)	approx. 120 W	DCAN: -//-, d e DN3 Value in order:# t 1.1
1.1	CAN data buses Voltages, low line	O	С	A1 L 10 (B.10)	Ignition: ON	approx. 2.3 V	DN3 Value in order:# t 1.2
1.2	CAN data buses Voltages, high line	o	С	A1 L 9 (B.9)	Ignition: ON	approx. 2.6 V	DN3